March 1995



## LM134/LM234/LM334 **3-Terminal Adjustable Current Sources**

## **General Description**

The LM134/LM234/LM334 are 3-terminal adjustable current sources featuring 10,000:1 range in operating current, excellent current regulation and a wide dynamic voltage range of 1V to 40V. Current is established with one external resistor and no other parts are required. Initial current accuracy is ±3%. The LM134/LM234/LM334 are true floating current sources with no separate power supply connections. In addition, reverse applied voltages of up to 20V will draw only a few dozen microamperes of current, allowing the devices to act as both a rectifier and current source in AC applications.

The sense voltage used to establish operating current in the LM134 is 64 mV at 25°C and is directly proportional to absolute temperature (°K). The simplest one external resistor connection, then, generates a current with  $\approx +0.33\%/^{\circ}C$ temperature dependence. Zero drift operation can be obtained by adding one extra resistor and a diode.

Applications for the current sources include bias networks, surge protection, low power reference, ramp generation, LED driver, and temperature sensing. The LM134-3/

LM234-3 and LM134-6/LM234-6 are specified as true temperature sensors with guaranteed initial accuracy of  $\pm 3^{\circ}C$ and  $\pm$  6°C, respectively. These devices are ideal in remote sense applications because series resistance in long wire runs does not affect accuracy. In addition, only 2 wires are required

The LM134 is guaranteed over a temperature range of -55°C to +125°C, the LM234 from -25°C to +100°C and the LM334 from 0°C to +70°C. These devices are available in TO-46 hermetic, TO-92 and SO-8 plastic packages.

## Features

- Operates from 1V to 40V
- 0.02%/V current regulation
- Programmable from 1 µA to 10 mA
- True 2-terminal operation
- Available as fully specified temperature sensor
- ±3% initial accuracy



© 1995 National Semiconductor Corporation TL/H/5697 RRD-B30M75/Printed in U. S. A.